



New Fox Part Number Codes - Crystals

This is to decode the new part numbering scheme. All combinations are not available.

Example FC8ACCBMM4.0

F	C8AC	C	B	M	M	4.0
Company	Model	Tolerance	Stability	Load Capacitance	Temp Code	Frequency
F=Fox	CABS=n/a	A=100ppm	A=100ppm	A=Series	A=0 to +50C	
	C8AC=FC	B=50ppm	B=50ppm	B=6pF	C=0 to +70C	
	C7BS=FD	C=30ppm	C=30ppm	C=4pF	D=-10 to +60C	
	C7AS=FE	D=25ppm	D=25ppm	D=8pF	E=-10 to +70C	
	C7CS=FH	E=20ppm	E=20ppm	E=10pF	F=-20 to +70C	
	C7DS=FL	F=15ppm	F=15ppm	G=12pF	M=-40 to +85C	
	C6BS=FMB	H=10ppm	H=10ppm	U=13pF	P=-40 to +105C	
	C8AQ=FQ1045A	L=5ppm	L=5ppm	J=15pF	I=-40 to +125C	
	C3BQ=FQ3225B	X=Overall	V=200ppm	K=16pF	T=-55 to +125C	
	C5AQ=FQ5032A			L=18pF		
	C5BQ=FQ5032B			M=20pF		
	C6AQ=FQ6035A			N=22pF		
	C6BQ=FQ6035B			P=27pF		
	C7AQ=FQ7050A			Q=30pF		
	C7BQ=FQ7050B			R=32pF		
	C6AS=FQA			S=33pF		
	C0BS=FX1612B			T=50pF		
	C1BS=FX216B			V=7pF		
	C1CS=FX216C			W=9pF		
	C2BS=FX252BS			X=14pF		
	C3BS=FX325BS			Y=19pF		
	C3BG=FX325BG					
	C4BS=FX425B					
	C5AX=FX532A					
	C5AG=FX532AG					
	C5AS=FX532AS					
	C5BS=FX532B					
	C5CG=FX532CG					
	C1BA=FXA2016B					
	C2BA=FXA2520B					
	C3BA=FXA3225B					
	C5AA=FXA5032AG					
	C5BA=FXA5032B					
	C7AA=FXA7050AG					

	C7BA=FXA7050B					
	C4SD=HC49SDLF					
	C4SX=HC49SPXLF					
	C4ST=HC49SLF					
	C9SD=HC49SSDLF					
	C9ST=HC49SSLF					
	C4UT=HC49ULF					
	C80T=HC80U					