



New Fox Part Number Codes - Crystals

This is to decode the new part numbering scheme. All combinations are not available.

Example FC8ACCBMM3.6864

F	C8AC	C	B	M	M	3	.	6864
Company	Model	Tolerance	Stability	Load Capacitance	Temp Code	Frequency before the decimal	Decimal or Custom Code	Frequency after the decimal
F=Fox	C8AC=FC	A=100ppm	A=100ppm	A=Series	A=0 to +50C	000	.=.	000000
	C7BS=FD	B=50ppm	B=50ppm	B=6pF	C=0 to +70C		A=TBD	
	C7AS=FE	C=30ppm	C=30ppm	C=4pF	D=-10 to +60C		B=TBD	
	C7CS=FH	D=25ppm	D=25ppm	D=8pF	E=-10 to +70C		C=TBD	
	C7DS=FL	E=20ppm	E=20ppm	E=10pF	F=-20 to +70C		D=TBD	
	C6BS=FMB	F=15ppm	F=15ppm	G=12pF	M=-40 to +85C			
	C8AQ=FQ1045A	H=10ppm	H=10ppm	U=13pF	P=-40 to +105C			
	C3BQ=FQ3225B	L=5ppm	L=5ppm	J=15pF	I=-40 to +125C			
	C5AQ=FQ5032A	X=Overall	V=200ppm	K=16pF	T=-55 to +125C			
	C5BQ=FQ5032B			L=18pF				
	C6AQ=FQ6035A			M=20pF				
	C6BQ=FQ6035B			N=22pF				
	C7AQ=FQ7050A			P=27pF				
	C7BQ=FQ7050B			Q=30pF				
	C6AS=FQA			R=32pF				
	C0BS=FX1612B			S=33pF				
	C1BS=FX216B			T=50pF				
	C1CS=FX216C			V=7pF				
	C2BS=FX252BS			W=9pF				
	C3BS=FX325BS			X=14pF				
	C1PT=FX-3LF			Y=19pF				
	C4BS=FX425B							
	C5AX=FX532A							
	C5AG=FX532AG							
	C5AS=FX532AS							
	C5BS=FX532B							
	C5CG=FX532CG							
	C1BA=FXA2016B							
	C2BA=FXA2520B							
	C3BA=FXA3225B							
	C5AA=FXA5032AG							
	C5BA=FXA5032B							
	C7AA=FXA7050AG							
	C7BA=FXA7050B							

	C4SD=HC49SDLF							
	C4SX=HC49SPXLF							
	C4ST=HC49SLF							
	C9SD=HC49SSDLF							
	C9ST=HC49SSLF							
	C4UT=HC49ULF							
	C80T=HC80U							



New Fox Part Number Codes - Watch Crystals

This is to decode the new part numbering scheme. All combinations are not available.

Example FKFSMEIHM0.032768

F	KFSM	E	I	H	M	0	.	032768
Company	Model	Tolerance	Stability	Load	Temp Code	Frequency before the decimal	Decimal or Custom Code	Frequency after the decimal
F=Fox	KFSM=FSMLF	E=20ppm	I=-0.04ppm/delta C2	B=6pF	D=-10 to +60C	000	.=.	000000
	KFSR=FSRLF			D=8pF	M=-40 to +85C		A=TBD	
	KFSX=FSXLF			H=12.5pF	I=-40 to +125C		B=TBD	
	K161=FX161			V=7pF			C=TBD	
	K122=FX122			W=9pF			D=TBD	
	K135=FX135							
	K13L=FX135L							
	K145=FX145							
	K255=FX255							
	K13A=FXA135							
	KT15=NC15LF							
	KT26=NC26LF							
	KS26=NC26SMLF							
	KM26=NC26SM-SLF							
	KT38=NC38LF							